

# THE DOCUMENT COMPANY XEROX

## DC230LP NetWare® 3.1x/4.1x Bindery Quick Install

### Installation Requirements:

If this is a Token Ring installation, the Token Ring card must be installed by your Xerox service representative and configured before performing this procedure. Refer to the *Token Ring Quick Install* card.

If running NLSP, be sure that RIP/SAP compatibility is configured on the same segment as the DC230LP.

**Note:** For an NDS installation, refer to the *NetWare 4.x NDS Quick Install* card.

### Before Installation:

- Perform the network installation for the printer using the appropriate NetWare utility (PCONSOLE).

**Note:** Define the printer as *Defined Elsewhere* or *Remote/Other*.

- Record the following information for use during setup at the DC230LP:

Print Server Name: \_\_\_\_\_





Print Server Password: \_\_\_\_\_

File Server Name: \_\_\_\_\_

Frame Type: \_\_\_\_\_


Poll Interval: \_\_\_\_\_

This installation procedure assumes that you know how to navigate through the menu system on the DC230LP Control Panel. Refer to the quick reference card, *Using the Menu System*, (701P96834) for assistance.


1. Connect the DC230LP to your network outlet or cable.
2. Access the System Administration menus:
  - a) Press **[Online]** to take the printer off line.  displays.
  - b) Press **[Menu]**.  displays.
  - c) Press **[▶]**, then press **[▲]** or **[▼]** until  displays.
  - d) Press **[▶]**.  displays.


- e) Use the **[▲]** and **[▶]** keys to enter **[2222]**.


**Note:** 2222 is the factory default password and may be changed to suit your needs. Refer to the *DC230LP System Administration Guide, Network Installation and Troubleshooting*.


- f) Press **[Enter]**.  displays.

3. Access the NetWare menus:


- a) Press **[▶]**.  displays.


- b) Press **[▼]** until  displays.

- c) Press **[▶]**.  displays.

- d) Press **[▼]** until  displays.

4. Enable NetWare:


- a) Press **[▶]**.  displays.

- b) Press **[▶]**.  displays.

# THE DOCUMENT COMPANY

## XEROX

### DC230LP NetWare® 3.1x/4.1x Bindery Quick Install


c) Press [▼].  displays.


d) Press [Enter]. \*\*SAVED\*\* displays momentarily, followed by



5. Select the appropriate Interface for your network:

**Note:** Token Ring will not be available as a selection unless it has been installed and configured.


a) Press [▼] until  displays. If Ethernet is the desired interface and it is already enabled, go to step 6.

b) If Token Ring is the required interface, press [▶], then press [▼] until  displays.


c) Press [Enter]. \*\*SAVED\*\* displays momentarily, followed by




6. Select the Frame Type for your network:

a) Press [▼] until  displays. If Ethernet II is the desired Frame Type, go to step 7.

b) Press [▶], then press [▼] until the required Frame Type displays.





c) Press [Enter]. \*\*SAVED\*\* displays momentarily, followed by



**IMPORTANT:** During the next two steps, be sure that the *Print Server Name* and *Print Server Password* are exactly the same as the values entered in PCONSOLE.

7. Enter the Print Server name:

a) Press [▼] until  displays.

b) Press [▶].  displays.


c) Press [▶] repeatedly until the cursor reaches the end of the entry. A tone sounds indicating when the last character has been reached.

d) Press [◀] repeatedly to delete the current entry.


e) Use the [▲] and [▶] keys to enter the Print Server name.

f) Press [▶] to move to the next character. Repeat this procedure to enter the entire Print Server Name.

g) Press [Enter]. \*\*SAVED\*\* displays momentarily, followed by



8. Enter the Print Server Password:

a) Press [▼] until  displays.

b) Press [▶].  displays.

c) Press [▶] repeatedly until the cursor reaches the last character. A tone sounds when the last character is reached.

d) Press [◀] repeatedly to delete the current entry.

e) Use the [▲] or [▼] key to enter the first character.

# THE DOCUMENT COMPANY XEROX

## DC230LP NetWare® 3.1x/4.1x Bindery Quick Install

f) Press [▶] to move to the next character. Repeat this procedure to enter the entire password.

g) Press [Enter]. \*\*SAVED\*\* displays momentarily, followed by

\*\*\*\*\*

9. Enter the File Server name:

**Note:** This step is REQUIRED to obtain the correct connectivity.

a) Press [▼] until  displays.

b) Press [▶].  displays.

c) Press [▶] repeatedly until the cursor reaches the end of the current entry. A tone sounds indicating when the last character has been reached.

d) Press [◀] repeatedly to delete each character.

e) Use the [▲] and [▶] keys to enter the File Server name.

f) Press [Enter]. \*\*SAVED\*\* displays momentarily, followed by

.

Verify that the name is correct.

g) To enter the names of additional File Servers, repeat step 9 for File Server 2, File Server 3, and File Server 4, as needed.

**Note:** Each additional File Server requires the identical Print Server Name and Password when setting them up in PCONSOLE.

10. Enter the Poll Interval:

a) Press [▼] until  displays.

b) Press [▶].  displays.

c) Press [▲] or [▼] to increase or decrease the setting to the desired number. The default setting is 5. The range is 1 to 240 seconds.

d) Press [Enter]. \*\*SAVED\*\* displays momentarily, followed by

.

11. Ensure that the NDS Tree is set to [-] (dash):

a) Press [▼].  displays.

b) If the current entry is a dash, go to step 12. If it is not a dash, press [▶]. The current entry displays with an underline below the character. Press [▲] or [▼] until the [-] (dash) displays.

c) Press [Enter]. \*\*SAVED\*\* displays momentarily, followed by

.


12. Ensure that the NDS Context is set to a [-] (dash):

a) Press [▼].  displays.


b) If the current entry is a dash, go to step 13. If it is not a dash, press [▶]. The current entry displays with an underline below the character. Press [▲] or [▼] until the [-] (dash) displays.


DC230LP NetWare® 3.1x/4.1x Bindery Quick Install

- c) Press **[Enter]**. **\*\*SAVED\*\*** displays momentarily, followed by



- 13.** Save all the settings:

- a) Press **[Online]**.  displays.

- b) Press **[Enter]**.  displays. The DC230LP will reboot, save the settings entered, and print a Configuration Report in approximately 3 minutes.

- 14.** Check the settings on the Configuration Report against those entered. The Pserver Password does not appear on the Configuration Report.

- 15.** At the client, install print drivers and map the printer in the usual manner. Refer to the CentreWare® manual, *Getting Started with Print and Fax Services*, for additional information.

Additional information on the NetWare setup can be found in the *DC230LP System Administration Guide, Network Installation and Troubleshooting*.