

Apple Macintosh (AppleTalk) Network Quick Install Card

Xerox Document Centre 240/255/265 LP/ST

Before You Start

If your printer is equipped with a Token Ring interface, use the **Token Ring Quick Install Card** supplied in this Quick Install Card set to set the Ring Speed and Source Routing settings for your environment.

Record the following information

AppleTalk Name _____

AppleTalk Zone _____

Go to the printer and...

1. Connect your Document Centre 240/255/265 to the network with the appropriate cabling.
2. Enter the *Tools* pathway
 - a) Press the **Access (A)** button.
 - b) On the keypad enter **1111** or the current password. Press the **Enter** button when finished. If your printer is an ST model press the **Go to Tools** button, otherwise skip to the next step.
 - c) The Touch Screen will be used for the remainder of the data entry.
3. Enable the AppleTalk protocol.

- a) Press the **Connectivity and Network Setup** button.
 - b) At the next screen, press the **Network Setup** button.
 - c) At the next screen, press the **AppleTalk** button.
 - d) At the next screen, press the **Protocol and Media** button.
 - e) At the next screen, press the **Enable** button to enable the AppleTalk protocol.
 - f) Press **Save**.
4. Assign a Name and Zone to your printer.
 - a) You will be returned to the previous screen. Press the **Name and Zone** button.

- b) At the next screen, press the **Printer Name** button and enter the name you want for the printer (this is the name that will appear in the Chooser on your workstations) using the touch panel keys. Then press **Save**.
- c) You will be returned to the previous screen. Press the **Zone Name** button, enter the desired text for this item using the touch panel keys, then press **Save** (the printer default is * which means the printer will appear in ALL zones).
- d) Press the **Exit Tools** button.

Apple Macintosh (AppleTalk) Network Quick Install Card

Xerox Document Centre 240/255/265 LP/ST

5. Wait a **MINIMUM of 7 minutes** for the printer to reset.
 - a) Obtain a **Configuration Report** page from your printer.
 - b) Review the **AppleTalk Settings:** area of the **Configuration Report** page and verify that **AppleTalk** is enabled, the **AppleTalk Name** is correct, the **AppleTalk Zone** is correct (if used).
 - c) From the documentation package supplied with your printer, retrieve the **CentreWare Network Services** CD-ROM (CD-ROM 2) and the document entitled **Getting Started with Print and Fax Services**. Proceed to the next section of this procedure called **Go to a Workstation and...**

Go to the workstation and...

1. Use the **CentreWare Network Services CD-ROM** (CD-ROM 2) to install print drivers and the Macintosh Naming Utility on the workstation. Details for this are found in the document supplied with your printer entitled **Getting Started with Print and Fax Services**.
2. Send a test job to the printer from an application program.
3. Check your test job for quality and use the problem solving section of the **Document Centre 240/255/265 Reference Guide** for resolving print defects.
4. If your job did not print see the Troubleshooting section of the **Network Installation and Troubleshooting Guide**.