



Fiery Patch Release Notes

General information

Defect ID number	1-1K3BBO
Product name	Fiery Network Controller for WorkCentre 7500 Series
Release date	18 June 2013

Files included in this release

File name	File size	Checksum
1-1K3BBO.ps	23.9 MB	4053361970

Issue(s) addressed with this release

- **1-1K3BBO: Composite patch 2 for Fiery Network Controller for Work Centre 7500 Series.**
- **1-1J41YD: Latest SMB patch 1-1I97N4 believed to cause instability in the Fiery**
- **1-1J5RGI: Patch 1-1I97N4 causing loss of connection when printing on port TCP 9200**
- **1-1HK48Y: Fiery patch to address DMP issue on iOS 6.**
- **1-1HU0SD: Patch to address Apache, PHP, Samba and OpenSSL security update.**
- **1-1JNJQC: Job printed from a MAC disappears.**
- **1-1JO296: Custom imposition template created with cws is not visible when setting up hotfolder**
- **1-1IEI2H : Fiery patch to address calibration issue for Heavyweight mediatype.**
- **1-1I97N4: Patch to address Scan to SMB issue when the Fiery connected.**



Before installing 1-1K3BBO.ps

- 1 Known issues listed below, read before installing **1-1K3BBO.ps** patch
 - **Apache version upgraded to 2.2.22**
 - **OpenSSL version upgraded to 0.9.8x**
 - **PHP version upgraded to 5.3.15**
 - **Samba version upgraded to 3.0.37**
 - **The defect 1-1JNJQC is reproducible interminally when same driver used after the patch.**
 - **Recommended to reinstall MAC driver on client after installing this patch.**
- 2 Following prerequisite(s) must be installed in the order specified before applying the **1-1K3BBO.ps** patch:
 - 1-1IAB3B.
- 3 Do **NOT** install any of the following patch(es) after installing the **1-1K3BBO.ps** patch. If you must install any of the patch(es) below, do so before installing the **1-1K3BBO.ps** patch:
 - None.
- 4 This patch is exclusive, it must be installed by itself, and the server must be rebooted or restarted once. After that, other patches can be applied to the server.

Patch installation instructions

- 1 Make sure that the Fiery controller has reached Idle.
- 2 Import the patch file **1-1K3BBO.ps** using Command WorkStation to the Direct connection.
- 3 You must wait until the file finishes processing and Command WorkStation or the LCD show Idle. This ensures the patch file is completely processed. User should wait one minute for complete installation of patch.
- 4 From Command WorkStation, choose Server, Reboot Server, or from the Fiery LCD, select Shut down, Reboot System.
- 5 Wait until the Fiery controller reaches Idle and print the configuration page.
- 6 Verify that the System Update Log contains the patch number **1-1K3BBO**.