

Mobile Print - Xerox® D95/D110/D125 Copier/Printer Update Process



702P00623

Overview

Each release of the Xerox Mobile Print Solution (Mobile Print) supports most EIP capable Multi-Function Printers (MFP) available at the time of the release. However newly launched or newly supported MFPs may become available between Mobile Print releases. This process will enable support as soon as possible.

Mobile Print uses the Xerox Global Print Driver® (X-GPD) for sending print jobs to the MFPs. The X-GPD uses a Device Compatibility Pack (DCP) as downloadable archive that adds product model support. Effectively, a DCP will allow the X-GPD to learn a new product without having to download and install an updated X-GPD print driver. A DCP does not necessarily enable new features such as a new finisher or a new job type.

Usage

- o This process is only applicable for adding Xerox® D95/D110/D125 Copier/Printer.
- o The Mobile Print system must be running version 1.5.2 or later.

Update Procedure

1. Ensure the Xerox® D95/D110/D125 Copier/Printer or Xerox® D95/D110/D125 Printer MFP is **On-Line** and obtain its TCP/IP address.
2. Log into the Mobile Print Server as a Windows Administrator.
3. Extract Printer Enablement files.
 - a. Navigate to the location of the Printer Enablement Update Zip file.
 - b. Right click on **1-5-2_XeroxD95_D110_D125_PrinterEnablementUpdate.zip**, select **Extract All**, select **Browse**, select **Computer**, select **(C:)** then select **OK**.
 - c. Validate: **Files will be extracted to this folder:** is **C:**, if not type in **C:** into the field.
 - d. Select **Extract**.
4. From the **C:\Mobile Print** folder, Run **GPD Update.reg** from the directory and select **Yes**, to allow changes to your registry, and then select **OK**.

5. Add a Temporary Printer.

Note: The exact steps to add a printer will differ from OS to OS; the steps are provided as an example of the process.

- a. On the Mobile Print Server, go to Devices and Printers (e.g., Windows Server 2003 & 2008: Control Panel > Printers and Faxes; Windows Server 2008 R2 and Windows 7: Control Panel > Hardware and Sound > Devices and Printers).
- b. Select **Add a printer**.
- c. Select **Add a local printer**.
- d. Select **Create a new port**.
- e. Select **Standard TCP/IP Port**, then select **Next**.
- f. Enter the D95/D110/D125 MFP's IP address in the **Hostname or IP Address** field.
- g. Deselect **Query the printer automatically select the driver to use**, then select **Next**.
- h. Set Manufacturer to **Xerox** (you may need to wait a full minute for list to appear).
- i. Select **Xerox Global Print Driver PS**, and then select **Next**.

Note: If there is more than one Xerox Global Print Driver selection, then select the one labeled, Xerox Global Print Driver PS version: 5246.13.0N[02082012].

- j. Select **Use the driver that is currently installed (recommended)**, and then select **Next**.

Note: Make Sure the **Printer name** is Xerox Global Print Driver PS.

- k. Name the new Printer **Temporary Printer**.
 - l. Select **Do Not Share this printer** checkbox, then select **Next**.
 - m. Deselect **the Set as the default printer** checkbox (if listed), then select **Finish**.
6. Check Temporary Printer status.
- a. In Devices and Printers, right-click on the **Temporary Printer** icon and select **Printer Properties**.
 - b. Select the **Options** tab.
 - c. Select **Xerox Update**.
 - d. You should receive a message **No update found**. Select **OK**.
 - e. Select **OK** to exit Printer Properties.
7. Copy Files.
- a. Navigate to **C:\Mobile Print** folder.

- b. From the C:\Mobile Print folder, copy the two files Xerox_Product_Mapping.xml and XMAH_2.2_5.246.13.1.cab to **C:\Mobile Print\GPD Update** folder.
- 8. Update Temporary Printer's Driver.
 - a. In Devices and Printers, right-click on the **Temporary Printer** icon and select **Printer Properties**.
 - b. Select the **Options** tab.
 - c. Select **Xerox Update**.
 - d. Select **Yes** to New driver update found for the Printer. Would you like to apply this specific product update to any similar Xerox Global Print Driver PS queues?
 - e. Select **OK** to exit Printer Properties.
 - f. You will see messages the other printer Queues are being updated.
- 9. Remove Temporary Printer.
 - a. Right click on the **Temporary Printer** icon and select **Remove Device**.
 - b. Select **Yes**.
- 10. Clean up.
 - a. From the C:\Mobile Print directory run **GPD Remove Setting.reg** and select **Yes** to allow changes to your registry.
 - b. Delete the folder **C:\Mobile Print**.

Additional Information

If you encounter any issues printing to Xerox® D95/D110/D125 Copier/Printer or Xerox®D95/D110/D125 with Mobile Print, you can verify that the driver was updated by validating that the MFP is available in the list of devices (exact steps will differ from OS to OS):

1. In Devices and Printers, right-click on **Xerox_GPD_PS_XX > Printer Properties > Xerox_GPD_PS_00**.
2. Select the **Options** tab.
3. Select **Configuration**.
4. Validate the Xerox D110-Copier-Printer and Xerox D125-Copier-Printer and Xerox D95-Copier-Printer are in the list.

You can reach Xerox Customer Support at <http://www.xerox.com> or by contacting your support representative.