



**Xerox HDI AutoCAD 2005
Print Driver
(Version 10.0.2)
for AccXES 10.0**
August 2004



Table of Contents

| | | |
|----------|-----------------------------------|----------|
| 1 | Trademark Acknowledgements | 3 |
| 2 | Release Content | 4 |
| 3 | New Release Features | 5 |
| 4 | Driver Installation | 6 |
| 5 | Driver Removal | 7 |
| 6 | Customer Issues Resolved | 8 |
| 7 | Known Issues | 9 |

1 Trademark Acknowledgements

XEROX®, XES™, Synergix™, The Document Company, and the identifying product names and numbers herein are trademarks of XEROX CORPORATION. All other product names mentioned herein are trademarks of their respective companies. All rights reserved.

Windows NT, Windows® 2000, Windows® XP Pro are registered trademarks of Microsoft Corporation.

AutoCAD is a registered trademark of Autodesk, Inc.

HDI is an acronym for Heidi Device Interface. Heidi is a registered trademark of Autodesk, Inc.

WinZip is a registered trademark of Nico Mak Computing, Inc.

2 Release Content

This release is provided as a self-extracting zip file. The self-extracting zip contains the following files:

| File | Version | Description |
|--------------|-------------------|---|
| XES8.HDI | 8.1.41.101 | Xerox AccXES HDI AutoCAD 2005 Driver DLL |
| XES8.DRC | | Xerox AccXES HDI AutoCAD 2005 Driver Capabilities File. |
| XES8RES.DLL | 8.0.16.86 | Xerox AccXES HDI AutoCAD 2005 Driver Resource DLL |
| DRV_XES.HLP | | Xerox AccXES HDI AutoCAD 2005 Driver help file. |
| DRV_XES.CNT | | Xerox AccXES HDI AutoCAD 2005 Driver help contents file. |
| DRV_XES.HIF | | Xerox AccXES HDI AutoCAD 2005 Driver install file (used by AutoDesk's Add-A-Plotter Wizard) |
| 8830ansi.fin | | Xerox AccXES Finisher definition file (ansi version) |
| 8830arch.fin | | Xerox AccXES Finisher definition file (arch version) |
| 8830iso.fin | | Xerox AccXES Finisher definition file (ISO version) |

There are 7 self-extracting zip files:

| | |
|------------|----------------------------|
| English | AccXES10.0HDI_2005_Enu.exe |
| French | AccXES10.0HDI_2005_Fra.exe |
| Italian | AccXES10.0HDI_2005_Ita.exe |
| German | AccXES10.0HDI_2005_Deu.exe |
| Spanish | AccXES10.0HDI_2005_Esp.exe |
| Portuguese | AccXES10.0HDI_2005_Ptg.exe |
| Russian | AccXES10.0HDI_2005_Rus.exe |

3 New Release Features

This release of the driver adds support for the following new printers:

- XEROX 6030 WIDE FORMAT
- XEROX 6050 WIDE FORMAT

This release supports the following new features:

- **Vector Minimum Line Width** - Use this setting to improve visibility of fine lines. Depending on your printer's resolution, lines that are only a few pixels wide may appear light and/or be difficult to see. This setting allows you to improve visibility by setting the minimum width of drawn lines anywhere from **1** (the default) to **10** pixels.

This release removes support for the following feature:

- Line Scale Mode

4 Driver Installation

The **English** version of the Xerox AccXES HDI AutoCAD 2005 Driver will be delivered as a self-extracting zip file called **AccXES10.0HDI_2005_Enu.exe**. Executing this program will extract the files to a default directory (c:\temp\AccXES10.0_HDI_2005) or to a directory of the user's choice. Use the AutoCAD 2005 Add-A-Plotter Wizard to add the printer

1. Start AutoCAD 2005
2. Click "File" and select "Plotter Manager"
3. Double click on the Add-A-Plotter Wizard Icon.
4. Follow the instructions on the screen until the "Have Disk" button is displayed. Click "Have Disk" and browse to the location where you unzipped the files (example: c:\temp\AccXES10.0_HDI_2005). Select DRV_XES.HIF and click "Open". The driver files will be updated on your AutoCAD 2005 system.
5. Select manufacturer Xerox.
6. Select the printer model you wish to install and follow the instructions.

The following files are installed when doing an **Add-A-Plotter** with the Have Disk button.

| Files | Destination |
|--------------|---|
| XES8.HDI | \DRV subdirectory of your AutoDesk product |
| XES8.DRC | \DRV subdirectory of your AutoDesk product |
| XES8RES.DLL | \DRV subdirectory of your AutoDesk product |
| 8830ansi.fin | \DRV subdirectory of your AutoDesk product |
| 8830arch.fin | \DRV subdirectory of your AutoDesk product |
| 8830iso.fin | \DRV subdirectory of your AutoDesk product |
| DRV_XES.HLP | \HELP subdirectory of your AutoDesk product |
| DRV_XES.CNT | \HELP subdirectory of your AutoDesk product |

5 Driver Removal

While AutoDesk provides a mechanism for removing the entire AutoCAD 2005 installation, they do not provide a mechanism for removing specific driver files. The 8 files shown as installed in the previous section, may be removed by exploring and deleting the individual files.

1. Start Windows Explorer.
2. Delete the XES8.HDI, XES8.DRC, XES8RES.DLL, 8830ansi.fin, 8830arch.fin, and 8830iso.fin files from the \DRV directory of AutoCAD 2005.
3. Delete the DRV_XES.CNT and DRV_XES.HLP files from the \HELP directory of AutoCAD 2005.
4. Exit Windows Explorer.
5. Empty your Recycle Bin and restart Windows.

6 Customer Issues Resolved

None at this time.

7 Known Issues

| Problem Description | Resolution |
|---|--------------------------|
| Grid fill and color Fill not printed on monochrome printers | Select 16Million colors. |

Prepared by:
Xerox Corporation
800 Phillips Road
Building 139-64A
Webster, New York 14580-9791
USA

©XEROX Inc. 2004. All rights reserved.

Printed in the United States of America

XEROX®, XEROX Wide Format 510DP, 721P, XES Synergix 8850 Digital Solution, Synergix Scan System, AccXES, and acronym, XEROX, are trademarks of XEROX CORPORATION.

08/2004