

The Document Company

XEROX

DC220/230ST AppleTalk® Quick Install

Before Installation:

Record the following information for use during setup at the DC220/230:

AppleTalk Printer Name:

Note: The DC220/230 will attach itself to the default zone of the local segment where it is connected.

1. Connect the DC220/230 to your network outlet or cable.
2. Enter System Administrator Setups:
 - a) Press the **[Access]** button on the Control Panel.
 - b) Enter the System Administrator password by typing **#22222** (# key and 22222) on the keypad and pressing **[Enter]** on the screen.

Note: #22222 is the factory default password and may be changed by your Xerox service representative to suit your needs.

3. Access the AppleTalk Setup screens:
 - a) On the screen display, press **[Print Setups]**.
 - b) Press **[Network Setups]**.
 - c) Press **[AppleTalk]**.
4. Enable AppleTalk:
 - a) Press **[Enablement]**.
 - b) Press **[Enabled]**.
 - c) Press **[Printer Name]**, then press **[Edit]** and use the keyboard displayed on the screen to enter the Printer Name for your network (31 characters, or less).
5. Press **[Save]**.
6. Press **[Save]**.
7. Press **[Exit]**. The DC220/230 will reboot and print a configuration sheet in approximately 3 minutes.
8. Check the settings on the configuration sheet against those that were entered.
9. To install the DC220/230 Macintosh® PPD:
 - a) Copy the DC220/230 Macintosh PPD from the CentreWare® CD to the *System Folder/Extensions/Printer Descriptions* folder.
 - b) Set up and configure the Print Driver via the Chooser.
 - c) Refer to the CentreWare® manual, *Getting Started with Print and Fax Services* for additional information.

Additional information on the AppleTalk installation can be found in the *DC220/230 System Administration Guide*.