

Software Patch 878503v1

VersaLink C415/B415/C625/B625



July 3, 2024

Purpose

This fix patch includes the following items to improve reliability of embedded fax:

- Sets the "FxAutoResendPolicy" to default value
- Disables "NVM_BATCH_SEND_OPT"
- Disables "RecvImgConfirmation"
- Sets "imageDataToControlFrameSilence" fax node to 300ms

File Location & Information

<http://www.support.xerox.com/support/xerox-versalink-series/file-download/enus.html?&contentId=166636>

Please review the entire Readme before installing any software.

Zip File Name	878503v1.zip
Patch Install File	878503v1.dlm
Patch Uninstall File	878503v1_un.dlm

Required Software Version(s)

If your current machine versions are not within the range noted below, contact your Xerox Customer Support representative to obtain the necessary software before installing the patch.

Device Model	System version requirements
VersaLink C415/B415/C625/B625	120.xxx.014.14400 120.xxx.014.16700

Installation Instructions

From a Web browser:

- Enter the device's IP address to access the Web UI. When prompted, login as Admin.
- Go to Properties->Security->Installation Policy->Allow Software Upgrades checkbox.
- Select Allow Software checkbox and apply.
- Go to Properties → Fleet Orchestrator → Create/Install File → Install a File.

- Select Software Upgrade File.
- Press [Browse] to locate the software file.
- Press [Install].

From USB:

- Copy the Patch files into USB.
- To install a patch file from USB, login as administrator.
- Insert USB flash drive into a USB port on the device.
- At the control panel touch screen, touch install File
- Browse for the patch file, then touch Install.
- To confirm the file installation, touch Install.
- You will get prompt as “Patch download complete. Remove the USB drive to continue the install and reboot the device.”
- Remove USB.

Software Installation will begin several minutes after the software file has been submitted to the machine. The installation progress can be monitored from the Local UI. When installation completes, the Patch version shown on the printed Configuration Report and in the machines embedded web server.