

Fiery Patch Release Notes

General information

Defect ID number	FIT156701
Product name	Xerox 550-560 Integrated Fiery v1.1
Release date	31 October 2013

Files included in this release

File name	File size	Checksum
Integrated_Fiery_550_560_SP8.ps	1.88 MB	2915726225

Issue(s) addressed with this release

- **FIT156701: Service Pack 8 for Xerox 550-560 Integrated Fiery.**
- FIT155703: Fiery patch to address active cancel button for mismatch paper job on engine LCD.
- 1-1KDR8X: Fiery patch to address point and print to virtual printer.
- 1-1K522Y: Fiery patch to address XPPS Fuser information issue.

Before installing Integrated_Fiery_550_560_SP8.ps



- 1 Known issues listed below, read before installing **Integrated_Fiery_550_560_SP8.ps** patch:
 - **The cancel button is now disabled for load paper jobs which is as per specification.**
 - **Cancel button works fine for jobs currently printing.**
 - **Launch Command WorkStation connect to the Fiery and Select Device Center Tab. Under Consumables we observe 3 K informations, where the K is average of K1 and K2. The same info will be observed in MIB browser and XDA-Lite.**
 - **This patch obsolete FIT155703, 1-1KDR8X and 1-1K522Y patches.**
- 2 The following prerequisite(s) must be installed in the order specified before applying the **Integrated_Fiery_550_560_SP8.ps** patch:
 - SP1
 - SP2
 - SP3
 - SP4



- SP5
 - SP6
 - SP7
- 3 Do NOT install any of the following patch(es) after installing the **Integrated_Fiery_550_560_SP8.ps** patch. If you must install any of the patch(es) below, do so before installing the **Integrated_Fiery_550_560_SP8.ps** patch:
- None.
- 4 This patch is exclusive, it must be installed by itself, and the server must be rebooted or restarted once. After that, other patches can be applied to the server.
-

Patch installation instructions

- 1 Make sure that the Fiery controller has reached Idle.
- 2 Import the patch file **Integrated_Fiery_550_560_SP8.ps** using Command WorkStation to the Direct connection.
- 3 You must wait until the file finishes processing and Command WorkStation or the LCD show Idle. This ensures the patch file is completely processed. User should wait one minute for complete installation of patch.
- 4 From Command WorkStation, choose Server, Reboot Server, or from the Fiery LCD, select Shut down, Reboot System.
- 5 Wait until the Fiery controller reaches Idle and print the configuration page.
- 6 Verify that the **System Update Log** contains the patch number **SP8**.