

Load document

To poll  
press [Start]

## Group Polling

Use this procedure to poll documents from multiple remote machines with one operation, using a preset Group Number (see "Presetting Group Numbers" earlier in this chapter).

A maximum of 50 groups can be preset for use with Multiple Polling Receptions.

**Note:** Group Polling is initiated when the Group Number is assigned to a One Touch key. (See "Presetting Group Numbers").

To poll documents from Multiple Remote Machines:

1. Open the Access Cover and press:

Polling



Poll one number

Enter fax number

2. Press:

Manual  
Group



Poll a group

Enter fax number

Speed dial Key  
or One Touch Key

3. Using the numeric keypad, **Speed Dial** or One Touch keys, enter the number and press **Enter** if necessary. Groups can also be entered if preset to a One Touch key.
4. Repeat step 3 until you enter in the Group Poll.
5. Press **Start**.

Poll a group  
Add Security Code?  
1. Yes  
2. No

## Polling

**Note:** All machines must use the same poll security code.

6. Select the Group Poll Security option:

To poll a group of numbers that do not require a Security Code, press **2**.

To enter a Security Code, press **1**.

**Poll a group**

**security code:**



7. Using the numeric keypad, enter the required Security Code, then press **Enter**.

The machine dials each number in the group and retrieves the document.