

Transmitting Documents

Send then Poll

This feature performs two operations, transmit and poll, in a single operation. If the remote machine has a document set to be polled, the polling document is received after your document is sent, during the same call (this is a one time procedure).

To set the Send then Poll feature:

1. Load the document face down in the Document Tray.
2. Select the desired **Resolution** and **Contrast**.
3. Press:



Send then poll
1. On
2. Off

4. Select the Send then Poll option:

To enable the Send then Poll feature, press **1**.

To disable the Send then Poll feature, press **2**, then go to step 6.

Send then poll
Add security code?
1. Yes
2. No

Transmitting Documents

5. Select the Security option:

To enter a Security Code, press **1**, then use the Numeric Keypad to enter a 4-digit code, and press **Enter**.

Free Memory	100%
Enter fax number	

If you do not wish to enter a security code, press **2**.

6. Press **Menu** to select additional fax options, or using one of the dialing methods, enter the fax number, then press **Enter** if necessary.

Free Memory	100%
Enter fax number	

The document is sent. If this feature is enabled, the document set to poll is received, then the machine returns to the Standby Mode.