

CopyCentre C165/175 DC UGD ReadMe  
Copyright (c) 2005 Xerox Ltd  
All Rights Reserved

For upgrading from 06.47.30.000 or later to 06.57.32.004.

Last updated 13:50, 9May05.

## 1. Introduction

-----  
The purpose of this Readme is to enable Technicians and System Administrators to upgrade a CopyCentre Digital Copier to version 06.57.32.004

The upgrade process will take up to half an hour. The CopyCentre will be inoperable during this time.

Please make sure that the CopyCentre is free of faults and jams before starting any part of the upgrade.

## 2. Upgrade Requirements

-----  
To perform this upgrade, the following will be required:

- a. The DC\_06-57-32-004-bot-c.ugd upgrade file
- b. A PC with the Xerox utilities installed, which must be at version 06.00.0004. A copy of the Xerox utilities is supplied with each CopyCentre machine; updates are available from [www.xerox.com](http://www.xerox.com).
- c. A type A->B USB cable of 1.5m length or less.

## 3. Upgrade Process

-----  
Downloading the new software set:

- a. Plug the USB cable from a USB port on the PC into the back of the CopyCentre.
- b. Power-on the CopyCentre.
- c. On your workstation, start the utilities tool from its installed location. If you get a USB Comms. Error message, unplug and then re-plug the USB cable.
- d. A window will appear on the PC, warning that jobs in the job queue will be lost; click "OK".

A window opens on the PC saying "Preparing the Xerox machine for software upgrade"; it should stay for approximately two minutes.

A window will then be displayed on the PC with the software currently installed on the CopyCentre.

- e. To proceed with the upgrade, select the "Select File" button; this will display a file browser.
- f. Select the file DC\_06-57-32-004-bot-c.ugd. The utilities tool will analyse this file, then display the software version about to be downloaded (06.57.32.004).
- g. Select "Upgrade" to confirm you want to install this software version.

After a few seconds, the files will begin to download. A message "Software Upgrade in progress" is shown on the CopyCentre User Interface. This window will also show the upgrade progress of all of the relevant modules on the CopyCentre machine.

The system will automatically reboot after the upgrade has finished.

- h. Once the upgrade is complete, confirm the new software version by pressing the Machine Status hard key on the CopyCentre User Interface, then select the "Machine Details" button. Check the system software version is now 06.57.32.004.

The CopyCentre is now ready for use.